

CAST Mains Switching Input Output Module

Part No. **CA731**



Overview

LPCB certified to EN54-17 & 18 and Kiwa Telefication certified to EN54-13.

A mains-switching version of our CA730 input output module.

Capable of switching 5A @ 230 V AC or 5A 30V DC.

Incorporates the functions of a switch monitor, zone monitor and output unit.

Can be configured to monitor any combination of the following:-

Up to 20 conventional detectors and 10 MCPs.

Any normally open switch with an EOL resistor fitted.

A simple normally open or closed switch (non-fault monitored).

Onboard short-circuit loop isolator.

6mA typical alarm current (1.7mA typical quiescent current) @ 22-40V DC.

Indicators for Loop polling, input faults and relay status.

Includes volt free changeover contacts that can be used to trigger rollershutter doors, gas shut-off valves, smoke vents, etc.

More Information

CAST' is the world's most-advanced 'distributed intelligence' fire alarm system protocol. Conceived, designed and realised by C-TEC as part of a five-year, multi-million pound project, it involved the creation of a powerful proprietary communication protocol (C-TEC Addressable System Technology, CAST) and multiple control panels & field devices. Now available to purchase, its key features include:

255 devices per loop.

Autonomous decision-making for faster response times.

Multiple type codes.

40V loop drive voltage.

Two 'soft' addressing options - automatic via the panel or manual via a powerful handheld programmer.

Powerful multi-level addressing facilitates easy device addition and swapped device identification.



- Multiple functionality at a single address (integrated devices) - coming soon.
- Volumes, tones & detector modes can be changed at compatible panels.
- High-speed data transmission and robust data transfer.
- Intrinsically EN54-13 compliant.
- Provides geographical location of short and open circuit faults (a short circuit isolator is included as standard in every CAST field device).
- Replace device function.
- Future seamless integration with other CAST life safety systems reducing energy, servicing, installation and repair costs.
- Designed and manufactured in the UK.

Technical Specifications

Approvals/certifications	LPCB certified to EN54-17 & 18 and Kiwa Telefication certified to EN54-13.
Compatibility	Compatible with C-TEC's XFP/ZFP CAST Addressable Fire Panels.
Application/operation	Incorporates the functions of a switch monitor, zone monitor and mains-switching output unit in one device.
Supply/operating voltage	22 to 40V DC.
Quiescent current	1.7mA typical.
Activation current	6mA @ 22 to 40V DC.
Auxiliary relays	One volt-free single pole changeover relay rated at 5A @ 230V AC or 5A @ 30V DC. Non-monitored. Clean contact.
Auxiliary inputs	One monitored input that can be set to operate as: (1) a single zone monitor to support up to 20 ActiV detectors and 10 MCPs or (2) a monitored normally-open switch, triggered by a 470R.
Indicators	Active (Lit Red): relay activated; monitored zone triggered or monitored switch closed; Polling (Flashing Red): communication check with the panel; Input Fault (Lit Yellow): fault detected on the monitored zone/switch.
Connections	Six 45° screw-type connectors that can take 0.5-2.5mm ² cable: +Ve & -Ve Loop In; +Ve & -Ve Loop Out; Zone +Ve & -Ve. Also includes N/O, N/C & C relay connections.
Product dimensions (mm)	147 W x 87H x 22 D mm. Can be mounted on a standard 25mm UK flush or surface double gang back box.
Construction & finish	ABS Polycarbonate plate with a 200 micron two-tone grey velvet polyester label with red and white detailing.
IP Rating	IP40 when correctly installed.
Weight	122g.
Operating conditions/temperature	-10°C to +55°C.



T 01942 322744 E sales@c-tec.co.uk
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom