

## UNIVERSAL COMMERCIAL FIRE COMMUNICATOR





MQ03-LTE-M-EN54



### **FUTURE-PROOF TECHNOLOGY**

Dual-SIM device, each SIM supporting multiple operators per country



### **FAST AND EASY INSTALLATION**

with any panel using Contact ID, SIA and Pulse 4+2



### **RELIABLE DATA REPORTING**

to any Alarm Receiving Center



### **IMPROVED RECURRING REVENUE**

Low flat-rate monthly fees for improved profitability



## **EV** MAIN FEATURES

REPORTING FORMATS – Dial Capture Interface supporting Contact ID, SIA and Pulse 4+2

**EXCEPTIONAL REDUNDANCY** – Dual-SIM device, each SIM supporting multiple operators per country

**SUPERVISED CONNECTIVITY** – 10 minute polling of the connection

ADMIN PORTAL – Online 24/7 device management & real-time status monitoring of user accounts

FULL EVENT REPORTING – Reliable reporting to any Alarm Receiving Center

**INSTALLER MOBILE APP** – Real-time on-site communication diagnostics and device configuration

UNIVERSAL PANEL COMPATIBILITY - Support of any panel via dial capture interface or digital inputs

### **SPECIFICATIONS**

- Multi-band CAT-M1 LTE 700/850/1700/1900/2100 MHz
- 2 Telco interfaces (Dial Capture): CID, SIA, Pulse 4+2
- 4 inputs & 2 outputs (programmable)
- Supply voltage: +12 to +29 VDC
- Consumption: Standby 50mA, Peak 200mA
- Dimensions: 63 x 90 x 32 mm
- · Weight: 73g without antenna

### **CERTIFICATIONS**

- EN54-21
- RED

# RCONTROL ADMIN MOBILE APP 24 180115 24 WOOMFONE 27.56V NI NZ NX NA OUTT OUTZ Device Details Name: Hame Sentable: 98906 Wirston: 81100 CMS Settings Report to CME: Nes Account No: Fine Read: 1234 1234, 1224 Did reporte Come: Addition/COMAFF) GIFFS Settings KCOD: 884000002189128189220 LAN: etabled Settings LAN: etabled Did Comes Settings LAN: etabled Did Comes Settings LAN: etabled Settings Setti